Technical Bulletin
No: 603 – Increasing Caller Output Level

Model: TI-101 **No:** 603

Subject: Increasing Caller Output Level **Date:** 8-24-94

Symptom: Caller output level is too low

Solution: Increase caller output gain

Procedure: The caller output level can be increased about 8 dB with two resistor changes. R75 should be 27k ohms and R62 should be 270K ohms. Check the values before you remove the board. Many older units have these values in place already

601 Heron Drive
Logan Township, NJ 08085
Phone: 856-467-8000 • Fax: 856-467-3044
http://www.radiosystems.com